ROEMTECH_®

PMA-245H

Plenum Mixer/Amplifier

Classroom audio has never been easier.

- HummBuster Technology
- Phenomenal Power
- Superb Performance



HummBuster Technology

The PMA-245H incorporates Roemtech's proprietary HummBuster technology on both inputs. This allows the installer or end user to simply "switch off" annoying hums or buzzes without affecting audio quality. The switches on the front panel are easily accessed and will effectively filter out hums and ground-loop issues that have traditionally plagued audio systems. Getting rid of audio noise has never been easier.

Phenomenal Power

With a true 45 watts of power, the PMA-245H will give you the audio clarity you need for your largest classrooms. In many environments, ambient background noise such as HVAC systems and hallway traffic is an issue. With the PMA-245H, these issues won't overpower your sound system.

Superb Performance

The PMA-245H has been designed with full-range performance in mind. Most amplifiers in this category do not put a lot of emphasis on accurate frequency performance. Roemtech has a different view, delivering crystal clear audio while maintaining impressive bass response. The PMA-245H handles the entire audio spectrum with superb accuracy. Featuring the latest innovations in class A/B technology, you will experience stunning performance while staying on budget.



Front Panel



Rear Panel

Specifications:

Power: 45watts @ 40hms
Freq. Response: 20Hz to 20kHz
Input 1: Stereo RCA - mixable
Input 2: Stereo 3.5mm - mixable
Outputs: Stereo or Mono Bridgeable
Power Supply: 18V @ 3.5Amps - 63watts

Operating Temp: -40F to +190F Weight: 1.6 lbs (amp only)

Amp Dimensions: 5.45"w x 4.05"d x 1.65"h

Warranty: 3 year standard